

## 2W Rotary Attenuator

- DC~6GHz, 1dB, 0.1dB Step, SMA Female to SMA Female

### Features:

The rotary step attenuator can adjust the power level of the microwave circuit in a stepped manner within a certain of frequency range without interrupting the circuit.

It can also be used as an internal attenuator for instruments and equipment, featuring small size, high precision, stability and reliability.



Product ID	MA-2SAF-6G-1D-1
<b>Electrical &amp; Mechanical Specifications</b>	
Frequency Range (MHz)	DC~6GHz
Attenuation Range(dB)	0-1
Attenuation Step(dB)	0.1
VSWR	≤1.50:1
Input Power (W)	2
Impedance (Ohm)	50
Connector Interface	SMA Female to SMA Female
<b>Environmental Specifications</b>	
Working Temperature	-55°C~+125°C
Overall Dimensions	62*43*30mm
Weight	0.2kg

### Outline Drawing

Dimensions are in millimeter

